

Operation of BEST ECG compatibility T8 LED tube
 Compatibility list: tested ballasts for use with ECG.

ECGsmart T8 2ft
 Replace 18W T8

Manufacturer	Model	Replace target fluorescent T8	Number of Lamps
Philips	HF-P 218 TL-D EII	18W	2
Philips	HF-P 218 TLD III IDC	18W	2
Philips	HF-P 3/4x18 TLD III IDC	18W	3
Philips	HF-P 3/4x18 TLD III IDC	18W	4
Philips	HF-P 3/4 18 TL-D EII	18W	3
Philips	HF-P 3/4 18 TL-D EII	18W	4
Philips	HF-S 118 TL-D II	18W	1
Philips	HF-S 218 TL-D II	18W	2
Philips	HF-S 3/4 18 TL-D II	18W	3
Philips	HF-S 3/4 18 TL-D II	18W	4
Philips	HF-P 118 TLD 220-240	18W	1
Philips	HF-P 118/136 TL-D III	18W	1
Philips	HF-S 118/136 TL-D II	18W	1
Philips	HF-P 218/236 TL-D III	18W	2
Philips	HF-S 218/236 TL-D II	18W	2
OSRAM	QTP8 1x18	18W	1
OSRAM	QTP8 2x18	18W	2
OSRAM	QT-FIT8 1x18	18W	1
OSRAM	QT-FIT8 2x18	18W	2
OSRAM	QT Fit 5/8 1x18-39	18W	1
OSRAM	QT-FIT 5/8 2x18-39	18W	2
OSRAM	QTP-OPTIMAL 118-40	18W	1
OSRAM	QTP-OPTIMAL 218-40	18W	2
OSRAM	QTP8 3x18 4x18	18W	3
OSRAM	QTP8 3x18 4x18	18W	4
OSRAM	QT-FIT8 3/4X18	18W	3
OSRAM	QT-FIT8 3/4X18	18W	4
OSRAM	QTi 1X14/24/21/39 GII	18W	1*
OSRAM	QTi 2X14/24/21/39 GII	18W	2*
OSRAM	QTi DALI 2x18 DIM	18W	2*
OSRAM	QTi DALI 3x18 DIM	18W	3*
OSRAM	QTi DALI 4x18 DIM	18W	4*
TRIDONIC	PC 1x18 T8 PRO Ip	18W	1
TRIDONIC	PC 2x18 T8 PRO Ip	18W	2
TRIDONIC	PC 3/4X18 TOP Ip	18W	3
TRIDONIC	PC 3/4x18 T8 PRO Ip	18W	4
TRIDONIC	PCA T8 EXCITE Ip Y, 3x18 W and 4x18 W	18W	3
TRIDONIC	PCA T8 EXCITE Ip Y, 3x18 W and 4x18 W	18W	4
TRIDONIC	PC 1/14-35/24/39 T5 PRO-M Ip	18W	1*
TRIDONIC	PC 2/14-21/24/39 T5 PRO-M Ip	18W	2*

HELVAR	EL1X18EF	18W	1
HELVAR	EL1X18NGN	18W	1
HELVAR	EL4X18NGN	18W	4
STAHL	6042/243-21	18W	1
STAHL	6042/243-22	18W	2
STAHL	6042/913-22	18W	2
STAHL	6042/923-21	18W	1
STAHL	6042/923-22	18W	2
VS	ELXe 218.526	18W	1
VS	ELXe 218.526	18W	2

The compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment, and the results can vary in certain field applications due to a number of factors.

Benson Energy Saving Technology does not take over any responsibility, warranty or liability that this results can also achieved by using the devices under other conditions, or when using successor models of the tested devices, or different models of the same manufacturer, or when using other LED tube types. The absence of a ballast from this chart does not necessarily imply incompatibility.

* Can only working with ECGsmart Series LED tubes

1-Jun-23
updated