

Operation of BEST ECG compatibility T8 LED tube
 Compatibility list: tested ballasts for use with ECG.

ECGsmart T8 4ft
 Replace 36W T8

Manufacturer	Model	Replace target fluorescent T8	Number of Lamps
Philips	HF-B 136 TLD 220-240	36W	1
Philips	HF-B 136 TLD EII 220-240	36W	1
Philips	HF-P 136 TL-D III IDC	36W	1
Philips	HF-P 236 TL-D III IDC	36W	2
Philips	HF-P 136 TLD EII 220-240	36W	1
Philips	HF-P 236 TLD 230-240	36W	2
Philips	HF-P 118/136 TL-D III	36W	1
Philips	HF-P 218/236 TL-D III	36W	2
Philips	HF-S 118/136 TL-D II	36W	1
Philips	HF-S 218/236 TL-D II	36W	2
Philips	HF-B 136/236 TLD EII 220-240	36W	1
Philips	HF-B 136/236 TLD EII 220-240	36W	2
Philips	HF-B 236 TLD EII 220-240	36W	2
Philips	HF-S 136 TL-D II	36W	1
Philips	HF-R TD 136 EII TL-D 1X36W T8 Touch and DALI	36W	1*
OSRAM	QT-FIT8 1x36	36W	1
OSRAM	QT-FIT8 2x36	36W	2
OSRAM	QTP8 1x36	36W	1
OSRAM	QTP8 2x36	36W	2
OSRAM	QTP-OPTIMAL 1x18-40	36W	1
OSRAM	QTP-OPTIMAL 2x18-40	36W	2
OSRAM	QT-FIT 5/8 2x18-39	36W	2*
OSRAM	QT-M 2x26-42/220-240 S	36W	2*
OSRAM	QTi 1X14/24/21/39 GII	36W	1*
OSRAM	QTi 2X14/24/21/39 GII	36W	2*
OSRAM	QTP-DL 2x36-40	36W	2
OSRAM	QTi DALI 1x36 DIM	36W	1*
OSRAM	QTi DALI 2x36 DIM	36W	2*
TRIDONIC	PC 1x36 T8 PRO lp	36W	1
TRIDONIC	PC 1x36 T8 TOP sl	36W	1
TRIDONIC	PC 1/36 T8 PRO sc	36W	1
TRIDONIC	PC 2x36 T8 TOP sl	36W	2
TRIDONIC	PC 2x36 T8 INDVSTRY	36W	2
TRIDONIC	PC 1/14-35/24/39 T5 PRO-M lp	36W	1*
TRIDONIC	PC 2/14-21/24/39 T5 PRO-M lp	36W	2*
HELVAR	2X36/40S	36W	2
HELVAR	EL 1X36/40/18S	36W	1
HELVAR	EL 1X36ngn	36W	1
HELVAR	EL1x36iDim	36W	8*
HELVAR	EL2x36iDim	36W	2*
AC	CSS-UV42PS	36W	1

STAHL	6042/243-21	36W	1
STAHL	6042/243-22	36W	2
STAHL	6042/983-22	36W	2
STAHL	6042/943-21	36	1
STAHL	6042/943-22	36W	2
VS	TYPE ELXC 136.207	36W	1
VS	TYPE ELXC 136.200	36W	1
VS	TYPE ELXC 236.202	36W	2
VS	TYPE ELXC 336.214	36W	3
VS	ELXe 238.527	36W	2
BAG	BCS36.1FX-11/220-240	36W	1

The compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment, and the results can vary in certain field applications due to a number of factors.

Benson Energy Saving Technology does not take over any responsibility, warranty or liability that this results can also achieved by using the devices under other conditions, or when using successor models of the tested devices, or different models of the same manufacturer, or when using other LED tube types. The absence of a ballast from this chart does not necessarily imply incompatibility.

* Can only working with ECGsmart Series LED tubes

1-Jun-23
updated